

Kamera SNG 1

"Mercedes Sprinter"

Technical details:

- ERA-Antenna (Ø 1,50m) with Nortel Dasa Mount
- EIRP 70 dBW
- Amplifier 2 x 400 Watt
- Dual Carrier or multiplexing or redundancy
- Uplink 13,75 GHz – 14,50 GHz,
- Downlink 10,70 GHz – 12,75 GHz, Ku-Band
- 2 x Thomson 4110 MPEG 2 (SD with BISS)
- Modulator/Upconverter 2 x Newtec 2080 LS (up to 40,0 Mbit/s interface rate, QPSK)
- Spectrum Analyzer Rhode & Schwarz
- Digital IRD Thomson and Tandberg TV
- Videorouter 16 x 16 SDI
- Auditorouter 16 x 16
- Digi Beta Sony DVW 500 AP
- IMX Sony MSW M2000P
- Camera Triax Chain 1: Sony BVP E30 with 17x lens- 16:9 or 4:3 switchable
- Videomixer Datavideo SE1000 HD/SD 6 Inputs
- Yamaha audio mixer 03D with Aux and Limit function
- 2 wireless microphones Sennheiser with earplugs
- Genlock generator with bars
- FischerPanda power generator 10 kW
- Isolation transformer
- UPC for primary transmitting chain
- A/D and D/A converter
- Telephone hybrid for coordination line and talkback via GSM



Vehicle:

- Mercedes Sprinter 416 CDI
- 2,7 l Diesel engine 115 kW (156 PS)
- Gross weight 4,6 t
- Power connector CEE 16A
- Diesel heating, AC, additional lighting
- Coffeemaker and fridge

Satellite capacity:

- Eutelsat
- Intelsat
- PanAmSat

www.SU-News.de

Telefon +49 / 700 - SUNEWSDE (+49/700-78639733) E-Mail: info@su-news.de

S.U.-News GmbH Satellite Uplink, Friedrich-List-Str. 112, 81377 München

Raiffeisenbank Hallertau (BLZ 701 696 93) Konto 192023

Handelsregister München HRB133865; St.Nr.132/137/90034; Ust.Id.Nr.DE813060006

Sitz: Au/Hallertau; Geschäftsführer Kathrin Keller, Markus Schillinger